

SAMSUNG

GSM TELEPHONE

SGH-P300

SERVICE *Manual*

GSM TELEPHONE



CONTENTS

1. Specification
2. Flow Chart of Troubleshooting
3. Exploded Views and Parts List
4. Electrical Parts List
5. PCB Diagrams
6. Block Diagrams

1. SGH-P300 Specification

1-1. GSM General Specification

	GSM900 Phase 1	EGSM 900 Phase 2	DCS1800 Phase 1	PCS1900
Freq. Band[MHz] Uplink/Downlink	890~915 935~960	880~915 925~960	1710~1785 1805~1880	1850~1910 1930~1990
ARFCN range	1~124	0~124 & 975~1023	512~885	512~810
Tx/Rx spacing	45MHz	45MHz	95MHz	80MHz
Mod. Bit rate/ Bit Period	270.833kbps 3.692us	270.833kbps 3.692us	270.833kbps 3.692us	270.833kbps 3.692us
Time Slot Period/Frame Period	576.9us 4.615ms	576.9us 4.615ms	576.9us 4.615ms	576.9us 4.615ms
Modulation	0.3GMSK	0.3GMSK	0.3GMSK	0.3GMSK
MS Power	33dBm~13dBm	33dBm~5dBm	30dBm~0dBm	30dBm~0dBm
Power Class	5pcl ~ 15pcl	5pcl ~ 19pcl	0pcl ~ 15pcl	0pcl ~ 15pcl
Sensitivity	-102dBm	-102dBm	-100dBm	-100dBm
TDMA Mux	8	8	8	8
Cell Radius	35Km	35Km	2Km	-


1-2. GSM Tx Power Class

TX Power control level	GSM900	TX Power control level	DCS1800	TX Power control level	PCS1900
5	33±2 dBm	0	30±3 dBm	0	30±3 dBm
6	31±2 dBm	1	28±3 dBm	1	28±3 dBm
7	29±2 dBm	2	26±3 dBm	2	26±3 dBm
8	27±2 dBm	3	24±3 dBm	3	24±3 dBm
9	25±2 dBm	4	22±3 dBm	4	22±3 dBm
10	23±2 dBm	5	20±3 dBm	5	20±3 dBm
11	21±2 dBm	6	18±3 dBm	6	18±3 dBm
12	19±2 dBm	7	16±3 dBm	7	16±3 dBm
13	17±2 dBm	8	14±3 dBm	8	14±3 dBm
14	15±2 dBm	9	12±4 dBm	9	12±4 dBm
15	13±2 dBm	10	10±4 dBm	10	10±4 dBm
16	11±3 dBm	11	8±4dBm	11	8±4dBm
17	9±3dBm	12	6±4 dBm	12	6±4 dBm
18	7±3 dBm	13	4±4 dBm	13	4±4 dBm
19	5±3 dBm	14	2±5 dBm	14	2±5 dBm
		15	0±5 dBm	15	0±5 dBm

2. SGH-P300 Flow Chart of Troubleshooting and Circuit Diagrams



2-1.Baseband


2-1-1. Power ON








2-1-2. Initial















2-1-4. Charging Part












2-1-5. Microphone Part


















2-1-7. LCD





. PLACEMENT [FRONT]



2-1-8. Camera






2-2.RF


2-2-1. GSM Receiver

CONTINUOUS RX ON
RF INPUT : 62CH
Cell power : -50dBm




2-2-2. DCS Receiver


CONTINUOUS RX ON
RF INPUT : 698CH
Cell power : -50dBm




2-2-3. PCS Receiver

CONTINUOUS RX ON
RF INPUT : 698CH
Cell power : -50dBm







2-2-4. GSM Transmitter




2-2-5. DCS Transmitter





2-2-6. PCS Transmitter






2-3-1. Bluetooth Part








3. SGH-P300 Exploded View and Parts List

3-1. Cellular phone Exploded View




3-2. Cellular phone Parts list

Design LOC		Discription	SEC Code
QAN01		ANTENNA-SGHP300	GH42-00655A
QAN04		MEC-INTENNA BRACKET	GH75-08141A
QAN06		PMO-INTENNA COVER V2	GH72-25058A
QBA00		NPR-BATT COVER	GH71-05607A
QBA01		INNER BATTERY PACK-800MAH,BLAC	GH43-02098A
QBA02		BATTERY-400MAH,BLK,ENG,M	GH43-02199A
QCA01		UNIT-CAMERA	GH59-02428A
QCK01		MEC-CAMERA KEY	GH75-08142A
QCR17		SCREW-MACHINE	6001-001460
QCR54		SCREW-MACHINE	6001-001645
QFR01		MEC-FRONT COVER	GH75-08138A
QKP01		MEC-KEYPAD MAIN	GH75-07517A
QLC01		LCD-SGHP300 MODULE	GH07-00775A
QMI03		MEC-CUSHION MIC RUBBER	GH75-08948A
QMO01		MOTOR DC-SGHP300	GH31-00203A
QMP01		PBA MAIN-SGHP300	GH92-02291A
QSP01		SPEAKER	3001-001832
QVO01		MEC-VOLUME KEY	GH75-08140A
QME01		UNIT-KEY FPCB ASSY	GH59-02492A
	QMI01	MICROPHONE-ASSY-SCHB340	GH30-00238A
QRE01		MEC-REAR COVER	GH75-08139A
	QRF03	PMO-EARJACK COVER V4	GH72-25063A

Description	SEC CODE
BAG PE	6902-000297
CBF INTERFACE-DATA LINK CABLE	GH39-00444A
ADAPTOR-SGHD800 TA(EU)	GH44-01060A
S/W UTILITY-SAMSUNGPCSTUDIOII2	GH46-00138A
UNIT-EARPHONE	GH59-02499A
LABEL(P)-WATER SOAK	GH68-02026A
MANUAL-USER	GH68-08602A
LABEL(R)-MAIN (EU)	GH68-08694A
CUSHION-CASE TA2 MA2	GH69-03420A
BOX(P)-UNIT MAIN (EU)	GH69-03423A
BOX(P)-MASTER MAIN	GH69-03571A
MPR-BOHO VINYL M/WIN	GH74-11424A
MPR-BOHO VINYL IF	GH74-13606A
MPR-BOHO VINYL WINDOW 2	GH74-15506A
MPR-CUSHION REAR SHEET	GH74-20162A

3-3. Test Jig (GH80-03307A)



3-3-1. RF Test Cable
(GH39-00283A)



3-3-2. DATA CABLE
(GH39-00444A)



3-3-3. Serial Cable



3-3-4. Power Supply Cable



3-3-5. Test Cable
(GH39-00304A)



3-3-6. TA
(GH44-01131A)



4. SGH-P300 MAIN Electrical Parts List

SEC Code	Design LOC	Description	STATUS
0403-001427	ZD404	DIODE-ZENER	SA
0403-001547	ZD400	DIODE-ZENER	SA
0403-001547	ZD403	DIODE-ZENER	SA
0406-001190	ZD402	DIODE-TVS	SA
0406-001208	ZD401	DIODE-TVS	SA
0407-000115	D500	DIODE-ARRAY	SA
0504-001049	TR400	TR-DIGITAL	SA
0505-001325	TR401	FET-SILICON	SA
0801-002529	TR402	IC-CMOS LOGIC	SA
1001-001306	U500	IC-ANALOG MULTIPLEX	SA
1001-001306	U501	IC-ANALOG MULTIPLEX	SA
1108-000024	UME200	IC-MCP	SA
1201-002223	PAM100	IC-POWER AMP	SA
1201-002233	U503	IC-AUDIO AMP	SA
1203-003046	U401	IC-BATTERY	SA
1203-003109	U405	IC-BATTERY	SA
1203-003169	U504	IC-MULTI REG.	SA
1203-003275	U403	IC-MULTI REG.	SA
1203-003428	U301	IC-DC/DC CONVERTER	SA
1203-003432	U100	IC-POSI.FIXED REG.	SA
1203-003434	U300	IC-DC/DC CONVERTER	SA
1203-003565	UCP300	IC-POWER SUPERVISOR	SA
1203-003768	U502	IC-POSI.FIXED REG.	SA
1203-003901	U404	IC-PWM CONTROLLER	SA
1204-002138	UCD500	IC-MELODY	SA
1205-002272	U200	IC-TRANSCEIVER	SA
1205-002433	UPL100	IC-TRANSCEIVER	SA
1205-002612	UCD400	IC-CODEC	SA
1205-002613	UCD501	IC-CODEC	SA
1404-001165	TH300	THERMISTOR-NTC	SA
1405-001082	V200	VARISTOR	SA
1405-001082	V400	VARISTOR	SA
1405-001082	V401	VARISTOR	SA
2007-000171	R109	R-CHIP	SA
2007-000171	R116	R-CHIP	SA

SEC Code	Design LOC	Description	STATUS
2007-000171	R408	R-CHIP	SA
2007-000171	R410	R-CHIP	SA
2007-000171	R502	R-CHIP	SA
2007-000171	R539	R-CHIP	SA
2007-000171	R540	R-CHIP	SA
2007-000171	R545	R-CHIP	SA
2007-000775	R514	R-CHIP	SA
2007-000775	R536	R-CHIP	SA
2007-001325	R519	R-CHIP	SA
2007-003025	R440	R-CHIP	SA
2007-003112	R400	R-CHIP	SA
2007-003112	R503	R-CHIP	SA
2007-003112	R507	R-CHIP	SA
2007-007107	R512	R-CHIP	SA
2007-007134	R501	R-CHIP	SA
2007-007134	R506	R-CHIP	SA
2007-007142	R518	R-CHIP	SA
2007-007142	R526	R-CHIP	SA
2007-007142	R528	R-CHIP	SA
2007-007142	R530	R-CHIP	SA
2007-007142	R531	R-CHIP	SA
2007-007192	R516	R-CHIP	SA
2007-007192	R517	R-CHIP	SA
2007-007308	R302	R-CHIP	SA
2007-007317	R523	R-CHIP	SA
2007-007317	R524	R-CHIP	SA
2007-007317	R535	R-CHIP	SA
2007-007489	R529	R-CHIP	SA
2007-007489	R534	R-CHIP	SA
2007-007528	R522	R-CHIP	SA
2007-007528	R525	R-CHIP	SA
2007-007528	R533	R-CHIP	SA
2007-007741	R310	R-CHIP	SA
2007-008045	R110	R-CHIP	SA
2007-008045	R311	R-CHIP	SA

SEC Code	Design LOC	Description	STATUS
2007-008045	R513	R-CHIP	SA
2007-008047	R101	R-CHIP	SA
2007-008047	R102	R-CHIP	SA
2007-008052	R301	R-CHIP	SA
2007-008052	R304	R-CHIP	SA
2007-008055	R113	R-CHIP	SA
2007-008055	R201	R-CHIP	SA
2007-008055	R203	R-CHIP	SA
2007-008055	R305	R-CHIP	SA
2007-008055	R411	R-CHIP	SA
2007-008055	R414	R-CHIP	SA
2007-008055	R416	R-CHIP	SA
2007-008055	R418	R-CHIP	SA
2007-008055	R510	R-CHIP	SA
2007-008117	R417	R-CHIP	SA
2007-008419	R403	R-CHIP	SA
2007-008419	R407	R-CHIP	SA
2007-008419	R409	R-CHIP	SA
2007-008419	R413	R-CHIP	SA
2007-008419	R420	R-CHIP	SA
2007-008419	R421	R-CHIP	SA
2007-008420	R543	R-CHIP	SA
2007-008420	R544	R-CHIP	SA
2007-008478	R205	R-CHIP	SA
2007-008483	R202	R-CHIP	SA
2007-008483	R204	R-CHIP	SA
2007-008483	R300	R-CHIP	SA
2007-008483	R306	R-CHIP	SA
2007-008516	R114	R-CHIP	SA
2007-008516	R200	R-CHIP	SA
2007-008516	R415	R-CHIP	SA
2007-008531	R520	R-CHIP	SA
2007-008531	R521	R-CHIP	SA
2007-008542	R115	R-CHIP	SA
2007-008579	R107	R-CHIP	SA

SEC Code	Design LOC	Description	STATUS
2007-008579	R108	R-CHIP	SA
2007-008588	R111	R-CHIP	SA
2007-008588	R401	R-CHIP	SA
2007-008588	R405	R-CHIP	SA
2007-008588	R406	R-CHIP	SA
2007-008808	R550	R-CHIP	SA
2007-009084	R402	R-CHIP	SA
2007-009084	R511	R-CHIP	SA
2007-009084	R515	R-CHIP	SA
2007-009111	R206	R-CHIP	SA
2007-009111	R207	R-CHIP	SA
2007-009115	R104	R-CHIP	SA
2007-009167	R303	R-CHIP	SA
2007-009170	R404	R-CHIP	SA
2007-009201	R100	R-CHIP	SA
2007-009206	R527	R-CHIP	SA
2007-009206	R532	R-CHIP	SA
2007-009211	R112	R-CHIP	SA
2203-000278	C124	C-CER,CHIP	SA
2203-000278	C143	C-CER,CHIP	SA
2203-000386	C213	C-CER,CHIP	SA
2203-000386	C214	C-CER,CHIP	SA
2203-000425	C131	C-CER,CHIP	SA
2203-000438	C529	C-CER,CHIP	SA
2203-000628	C123	C-CER,CHIP	SA
2203-000654	C515	C-CER,CHIP	SA
2203-000812	C538	C-CER,CHIP	SA
2203-000812	C539	C-CER,CHIP	SA
2203-000812	C541	C-CER,CHIP	SA
2203-000812	C546	C-CER,CHIP	SA
2203-000870	C142	C-CER,CHIP	SA
2203-000885	C526	C-CER,CHIP	SA
2203-001405	C516	C-CER,CHIP	SA
2203-002668	C113	C-CER,CHIP	SA
2203-002668	C141	C-CER,CHIP	SA

SEC Code	Design LOC	Description	STATUS
2203-002677	C103	C-CER,CHIP	SA
2203-002677	C104	C-CER,CHIP	SA
2203-002677	C105	C-CER,CHIP	SA
2203-002677	C114	C-CER,CHIP	SA
2203-002677	C115	C-CER,CHIP	SA
2203-005393	C140	C-CER,CHIP	SA
2203-005552	C106	C-CER,CHIP	SA
2203-005552	C112	C-CER,CHIP	SA
2203-005682	C109	C-CER,CHIP	SA
2203-005682	C110	C-CER,CHIP	SA
2203-005682	C122	C-CER,CHIP	SA
2203-005682	C421	C-CER,CHIP	SA
2203-005682	C422	C-CER,CHIP	SA
2203-005682	C423	C-CER,CHIP	SA
2203-005682	C430	C-CER,CHIP	SA
2203-005682	C431	C-CER,CHIP	SA
2203-005682	C432	C-CER,CHIP	SA
2203-005682	C433	C-CER,CHIP	SA
2203-005682	C434	C-CER,CHIP	SA
2203-005682	C435	C-CER,CHIP	SA
2203-005682	C436	C-CER,CHIP	SA
2203-005682	C437	C-CER,CHIP	SA
2203-005719	C126	C-CER,CHIP	SA
2203-005736	C100	C-CER,CHIP	SA
2203-005736	C102	C-CER,CHIP	SA
2203-005736	C134	C-CER,CHIP	SA
2203-005736	C135	C-CER,CHIP	SA
2203-005736	C136	C-CER,CHIP	SA
2203-005736	C137	C-CER,CHIP	SA
2203-005736	C316	C-CER,CHIP	SA
2203-005736	C441	C-CER,CHIP	SA
2203-005736	C548	C-CER,CHIP	SA
2203-005736	C549	C-CER,CHIP	SA
2203-005779	C446	C-CER,CHIP	SA
2203-005779	C447	C-CER,CHIP	SA

SEC Code	Design LOC	Description	STATUS
2203-005806	C449	C-CER,CHIP	SA
2203-005806	C450	C-CER,CHIP	SA
2203-006141	C401	C-CER,CHIP	SA
2203-006190	C536	C-CER,CHIP	SA
2203-006190	C537	C-CER,CHIP	SA
2203-006190	C544	C-CER,CHIP	SA
2203-006190	C545	C-CER,CHIP	SA
2203-006194	C108	C-CER,CHIP	SA
2203-006194	C117	C-CER,CHIP	SA
2203-006194	C132	C-CER,CHIP	SA
2203-006194	C133	C-CER,CHIP	SA
2203-006194	C138	C-CER,CHIP	SA
2203-006194	C139	C-CER,CHIP	SA
2203-006194	C203	C-CER,CHIP	SA
2203-006194	C204	C-CER,CHIP	SA
2203-006194	C207	C-CER,CHIP	SA
2203-006194	C208	C-CER,CHIP	SA
2203-006194	C211	C-CER,CHIP	SA
2203-006194	C212	C-CER,CHIP	SA
2203-006194	C301	C-CER,CHIP	SA
2203-006194	C303	C-CER,CHIP	SA
2203-006194	C318	C-CER,CHIP	SA
2203-006194	C319	C-CER,CHIP	SA
2203-006194	C414	C-CER,CHIP	SA
2203-006194	C540	C-CER,CHIP	SA
2203-006257	C337	C-CER,CHIP	SA
2203-006257	C444	C-CER,CHIP	SA
2203-006260	C524	C-CER,CHIP	SA
2203-006260	C525	C-CER,CHIP	SA
2203-006305	C415	C-CER,CHIP	SA
2203-006305	C416	C-CER,CHIP	SA
2203-006324	C116	C-CER,CHIP	SA
2203-006324	C125	C-CER,CHIP	SA
2203-006324	C304	C-CER,CHIP	SA
2203-006324	C400	C-CER,CHIP	SA


SEC Code	Design LOC	Description	STATUS
2203-006379	C509	C-CER,CHIP	SA
2203-006379	C510	C-CER,CHIP	SA
2203-006399	C309	C-CER,CHIP	SA
2203-006399	C311	C-CER,CHIP	SA
2203-006399	C312	C-CER,CHIP	SA
2203-006399	C313	C-CER,CHIP	SA
2203-006399	C314	C-CER,CHIP	SA
2203-006399	C321	C-CER,CHIP	SA
2203-006399	C338	C-CER,CHIP	SA
2203-006399	C404	C-CER,CHIP	SA
2203-006399	C408	C-CER,CHIP	SA
2203-006399	C409	C-CER,CHIP	SA
2203-006399	C410	C-CER,CHIP	SA
2203-006399	C412	C-CER,CHIP	SA
2203-006399	C413	C-CER,CHIP	SA
2203-006399	C419	C-CER,CHIP	SA
2203-006399	C440	C-CER,CHIP	SA
2203-006399	C511	C-CER,CHIP	SA
2203-006399	C512	C-CER,CHIP	SA
2203-006399	C522	C-CER,CHIP	SA
2203-006399	C530	C-CER,CHIP	SA
2203-006399	C552	C-CER,CHIP	SA
2203-006399	C554	C-CER,CHIP	SA
2203-006399	C555	C-CER,CHIP	SA
2203-006399	C556	C-CER,CHIP	SA
2203-006399	C557	C-CER,CHIP	SA
2203-006423	C111	C-CER,CHIP	SA
2203-006423	C118	C-CER,CHIP	SA
2203-006423	C120	C-CER,CHIP	SA
2203-006423	C128	C-CER,CHIP	SA
2203-006423	C130	C-CER,CHIP	SA
2203-006423	C200	C-CER,CHIP	SA
2203-006423	C202	C-CER,CHIP	SA
2203-006423	C205	C-CER,CHIP	SA
2203-006423	C206	C-CER,CHIP	SA


SEC Code	Design LOC	Description	STATUS
2203-006423	C209	C-CER,CHIP	SA
2203-006423	C210	C-CER,CHIP	SA
2203-006423	C216	C-CER,CHIP	SA
2203-006423	C233	C-CER,CHIP	SA
2203-006423	C300	C-CER,CHIP	SA
2203-006423	C302	C-CER,CHIP	SA
2203-006423	C320	C-CER,CHIP	SA
2203-006423	C406	C-CER,CHIP	SA
2203-006423	C407	C-CER,CHIP	SA
2203-006423	C411	C-CER,CHIP	SA
2203-006423	C420	C-CER,CHIP	SA
2203-006423	C438	C-CER,CHIP	SA
2203-006423	C439	C-CER,CHIP	SA
2203-006423	C445	C-CER,CHIP	SA
2203-006423	C448	C-CER,CHIP	SA
2203-006423	C503	C-CER,CHIP	SA
2203-006423	C505	C-CER,CHIP	SA
2203-006423	C514	C-CER,CHIP	SA
2203-006423	C518	C-CER,CHIP	SA
2203-006423	C519	C-CER,CHIP	SA
2203-006423	C520	C-CER,CHIP	SA
2203-006423	C521	C-CER,CHIP	SA
2203-006423	C527	C-CER,CHIP	SA
2203-006423	C531	C-CER,CHIP	SA
2203-006423	C547	C-CER,CHIP	SA
2203-006556	C101	C-CER,CHIP	SA
2203-006556	C121	C-CER,CHIP	SA
2203-006556	C217	C-CER,CHIP	SA
2203-006556	C218	C-CER,CHIP	SA
2203-006556	C219	C-CER,CHIP	SA
2203-006556	C220	C-CER,CHIP	SA
2203-006556	C221	C-CER,CHIP	SA
2203-006556	C222	C-CER,CHIP	SA
2203-006556	C223	C-CER,CHIP	SA
2203-006556	C224	C-CER,CHIP	SA

SEC Code	Design LOC	Description	STATUS
2203-006556	C225	C-CER,CHIP	SA
2203-006556	C226	C-CER,CHIP	SA
2203-006556	C227	C-CER,CHIP	SA
2203-006556	C228	C-CER,CHIP	SA
2203-006556	C229	C-CER,CHIP	SA
2203-006556	C230	C-CER,CHIP	SA
2203-006556	C231	C-CER,CHIP	SA
2203-006556	C232	C-CER,CHIP	SA
2203-006562	C129	C-CER,CHIP	SA
2203-006562	C215	C-CER,CHIP	SA
2203-006562	C418	C-CER,CHIP	SA
2203-006562	C425	C-CER,CHIP	SA
2203-006562	C500	C-CER,CHIP	SA
2203-006562	C501	C-CER,CHIP	SA
2203-006562	C532	C-CER,CHIP	SA
2203-006562	C542	C-CER,CHIP	SA
2203-006562	C543	C-CER,CHIP	SA
2203-006636	C417	C-CER,CHIP	SA
2203-006648	C127	C-CER,CHIP	SA
2203-006648	C201	C-CER,CHIP	SA
2203-006648	C317	C-CER,CHIP	SA
2203-006648	C426	C-CER,CHIP	SA
2203-006825	C305	C-CER,CHIP	SA
2203-006825	C306	C-CER,CHIP	SA
2203-006838	C310	C-CER,CHIP	SA
2203-006838	C533	C-CER,CHIP	SA
2404-001268	TA500	C-TA,CHIP	SA
2404-001274	TA400	C-TA,CHIP	SA
2404-001339	TA501	C-TA,CHIP	SA
2404-001339	TA502	C-TA,CHIP	SA
2404-001352	TA503	C-TA,CHIP	SA
2404-001352	TA504	C-TA,CHIP	SA
2404-001380	TA401	C-TA,CHIP	SA
2404-001380	TA402	C-TA,CHIP	SA
2404-001394	C443	C-TA,CHIP	SA

SEC Code	Design LOC	Description	STATUS
2404-001394	TA300	C-TA,CHIP	SA
2404-001394	TA403	C-TA,CHIP	SA
2404-001394	TA505	C-TA,CHIP	SA
2404-001394	TA506	C-TA,CHIP	SA
2404-001411	TA100	C-TA,CHIP	SA
2703-001231	L402	INDUCTOR-SMD	SA
2703-001512	L104	INDUCTOR-SMD	SA
2703-002205	L103	INDUCTOR-SMD	SA
2703-002532	L102	INDUCTOR-SMD	SA
2703-002547	L100	INDUCTOR-SMD	SA
2703-002734	L300	INDUCTOR-SMD	SA
2703-002734	L301	INDUCTOR-SMD	SA
2703-002785	L109	INDUCTOR-SMD	SA
2703-002880	L101	INDUCTOR-SMD	SA
2801-004225	OSC400	CRYSTAL-SMD	SA
2801-004373	OSC200	CRYSTAL-SMD	SA
2801-004426	OSC100	CRYSTAL-SMD	SA
2809-001284	TCX100	OSCILLATOR-VCTCXO	SA
2901-001308	F301	FILTER-EMI SMD	SA
2901-001308	F302	FILTER-EMI SMD	SA
2901-001308	F303	FILTER-EMI SMD	SA
2901-001308	F304	FILTER-EMI SMD	SA
2911-000010	MOD100	DUPLEXER-FEM	SA
3301-001659	L500	BEAD-SMD	SA
3301-001659	L501	BEAD-SMD	SA
3301-001806	L106	BEAD-SMD	SA
3705-001358	RFS100	CONNECTOR-COAXIAL	SA
3708-002171	SOC300	CONNECTOR-FPC/FFC/PIC	SA
3709-001391	SIM400	CONNECTOR-CARD EDGE	SA
3710-002306	IFC405	SOCKET-INTERFACE	SA
3711-005541	HDC401	HEADER-BOARD TO BOARD	SA
3711-005643	HDC400	HEADER-BOARD TO BOARD	SA
3711-006003	BTC400	CONNECTOR-BATTERY	SA
4302-001158	BAT300	BATTERY-LI(2ND)	SA
4709-001368	MOD101	BLUETOOTH MODULE	SA
GH09-00038A	UCP200	IC MICOM	SA
GH59-02475A	LED400	UNIT-PL FLASH	SA


5. SGH-P300 PCB Diagrams






6. SGH-P300 Block Diagrams

RF PART





**SAMSUNG
ELECTRONICS**

